



telsat

High Power FM Compact Transmitters

SERIES MKRT-D

marKoni: The New FM Frontier!

The philosophy of our transmitters provides high reliability and efficiency, delivering a fantastic pure sound sensation thanks to our brilliant integrated digital modulator, which implements an innovative direct-RF synthesis algorithm, with sub-Hz accuracy onto an FPGA-based digital processing core.

Thanks to the big full-colour LED touch screen display it is possible to check or change all the system parameters.

Key Features

- Crystal Digital Sound purity
- Fully Digital Signal Processing
- Embedded RDS generator
- Auto-calibration at power-on
- Unbeatable price/performance
- Lifetime upgradable firmware
- Absolutely no analogue trimming points
- Single-chip Digital Processing for the maximum compactness
- Minimum BOM, maximum long-term reliability
- Fully remotely controllable by Web/SNMP interface
- 1pps and 10MHz inputs for Synchro FM Operation
- 2 Redundant Inputs
- E-mail Alert

Configurations

- Passive Reserve
- N+1 Reserve



▲ Front panel detail



▲ Rear panel

marKoni

Specifications



▲ Touch-screen display

TYPE	POWER
MKRT-D3000	3kW
MKRT-D5000	5kW

SIGNAL PROCESSING SECTION

FM Carrier Generation	NCO-based synthesis
FM Modulation	Fully digital
Stereo Coder	Fully digital, integrated
Input Audio Limiter	Proprietary integrated Soft Limiter
Digital Processing Resolution	Real-time internal 32-bit digital processing
RDS Generator	Fully integrated
Monitoring Output Signal	Fully digitally generated

INPUT SECTION

- Analog L/R Input	30Hz - 15kHz (integrated digital stereo coder) 0dBu nominal (adjustable from -12dBu to +12dBu) 600 Ohm/10 kOhm balanced/unbalanced
- Analog MPX and SCA Input	30Hz - 100kHz 0dBu nominal 10 kOhm unbalanced 40kHz - 100kHz 2Vpp nominal for ±7.5kHz deviation 10 kOhm unbalanced
- Digital L/R Input	AES/EBU (XLR Female), S/PDIF (BNC) 110 Ohm 75 Ohm
- RX-IP Audio Decoder (Option)	Unicast RTP/UDP compatible receiver HE-AAC (v.1 and v.2), MPEG-1 Layer 3 or raw PCM RJ45
- Audio Delay	0 - 4ms, step 1ms

OUTPUT SECTION

RF Output Frequency (FM/OIRT bands)	87.5MHz - 108MHz step 1Hz, ±1ppm frequency stability / OIRT on request
Output Interface/Impedance	7/8" Flange type (3kW-5kW)
Pilot Carrier Frequency	19kHz ±0.001Hz
Pilot Carrier Level	0-12% modulation in 0.1% steps
Pilot Carrier Output	1Vpp digitally synthesized
MPX Analogue Output	0dBu from integrated digital stereo coder
19kHz and 38kHz Tone Suppression	< -63dB
THD (30Hz-15kHz)+N	< 0.1%
Synchronous AM	Better than -60dB
Asynchronous AM	Better than -70dB
Mono SNR RMS	Better than -85dB
Stereo SNR RMS	Better than -80dB
L/R and R/L Crosstalk	> 50dB (60dB typ.)
M/S and S/M Crosstalk	> 45dB full-band
Pilot Carrier Phase	User-adjustable (step <1°)
Frequency Deviation Range	User-adjustable 0 to ±200kHz
Pre-emphasis	Flat, 50us or 75us

GENERAL

Physical	Case 19"-4U
Remote Control Port	RS232/RS485
Remote Control Options	PSTN, GSM (optional), Ethernet, SNMP
Front Panel User Interface	LCD full color touch screen display
Power Supply Voltage	High power, 230V or 400V, ±15%
Typical Efficiency at 98MHz	74%
Operating Temperature	0 - 45°C

www.markoni.it

TELSAT Srl - Via Ezio Vanoni, 6 - 20037 Paderno Dugnano (MI) - **ITALY**
ph +39.02.99048430 - fax +39.02.99048312 - www.telsat.it - telsat@telsat.it

